

# PCWork PCW06A Voltage Detector

## Easy voltage detection: PCW06A Voltage Detector

Allows secure testing and voltage break detection

- CAT III 1000V, CAT IV 600V
- NCV (non-contact voltage) test
- Dual measuring mode: 12-1000V (sensitive mode) or 48-1000V (standard mode)
- Double insulation
- Buzzer & LED light indicate phase or neutral conductor
- Bi-color backlight LCD display (red & green) with bar graph (indicates voltage strength)
- Bright LED flashlight
- Practical holding clip (like a pen)
- Low battery indication & auto power-off function
- Great packaging design and manual with pictures in various languages: EN, GER, ES, FR, PT, PL, IT



# PCW06A Technical Data:

AC Voltage:	12-1000V AC, 50/60 Hz
Operating Temperature:	0-40°C
Storage Temperature:	-10-50°C
Humidity:	≤95%
Operating Altitude:	≤2000m
Power Supply:	2*1.5V AAA Batteries; Auto Power-Off function
Size:	155*19*22mm
Weight:	60g
Safety Rating:	CE; EN61010-1; EN61326-1; EN61000-3-2,3-3; ROHS: 2011/65/EU and amendment 2015/863/EU









# PCW06A Pictures:

